

# TABLET MODEL ADOC T10




## SPECIFICATIONS

---

GENERAL	<p><b>Format:</b> tablets</p> <p><b>Networks:</b> GSM900/1800MHz UMTS900/2100MHz LTE B1, B3, B7, B8, B20, B28, B38</p> <p><b>Languages:</b> Spanish, English, Portuguese, Catalan, Galician and Basque (among others)</p> <p><b>Antenna:</b> integrated inside the terminal</p>
PROCESSOR	<p><b>CPU:</b> SC9863A Cortex A55 Octa-core 1.6Ghz 64bits</p> <p><b>GPU:</b> PowerVR GE8322 / IMG8322 1920 x 1200</p>
OS	<p>OS: Android 11 (upgradable to Android 12) Certificate: CTS and GMS (Google). Software updates and security patches via GOTA (Google over the air) up to 5 years. Listing: Zero touch</p>
DIMENSIONS AND WEIGHT	<p><b>Dimensions:</b> 244 * 172.9 * 9.3mm</p> <p><b>Weight:</b> 490 g</p>
SCREEN	<p><b>Size:</b> 10.1"</p> <p><b>Type:</b> IPS</p> <p><b>Resolution:</b> 1920*1200 and 280nits</p> <p>Capacitive multi-touch</p>
CONNECTIVITY	<p>Bluetooth® 5.0 Wi-Fi 802.11 a/b/g/n/ac, 2.4GHz/5Ghz bands Hotspot functionality</p>
CONNECTORS	<p>Jack 3.5 for use with headphones Micro SIM card slot MicroSD card slot</p>
MEMORY	<p>RAM Memory: 3GB DDR3 ROM memory: 32GB Compatible with microSD memory up to 128GB</p>
CAMERA	<p>2MPx Front Camera 5MPx rear camera Rear flash</p>

---

<b>AUDIO</b>	1 built-in microphone 2 integrated speakers 0.8W of 8Ω Integrated audio controller
<b>SENSORS</b>	Accelerometer GPS Brightness sensor
<b>SERVICES SUPPORTED</b>	SMS Call functionalities: redial, put on hold, transfer and conference up to 6 participants Call services: fixed dialling, call forwarding, call waiting, call barring SW upgrade via DROP
<b>BATTERY</b>	Type: Li-ion Capacity: 5,000mAh Rated voltage: 3.8V Removable battery*
<b>OTHERS FEATURES</b>	SIM tool FM Radio Multimedia Email (POP3/IMAP/Exchange)
<b>CERTIFICATIONS</b>	CE RoHS GMS GCF**
<b>CONTENTS</b>	1. Main unit 2. Protective case 3. Guarantee letter 4. User manual 5. Charger 6. USB type-c cable



1



2




3



4



5



6

\*Para extraer la batería se requiere de un técnico homologado, ya que es necesario abrir la tablet  
 \*\*Certificación en proceso